

5025-00

PHT Dual Pneumatic Head Wire Twister

Designed to be a heavy-duty multiple assembly Wire Twister. The PHT utilizes the same simple to use method as our standard MT.2 wire twister with a big difference. The PHT has a much more powerful motor and two mandrels to twist heavy gauge wires such as 10 and 12 gauge but will still delicately handle wires a small as 30-32 gauge and can twist TWO assemblies at the same time!

The operator easily inserts the wires into the Adapter Collet and presses the first stage "clamp" foot switch located near the machine. The operator then steps back pulling the wires straight and presses the second stage "Twist" footswitch, this activates the Twist cycle. When the number of twists are completed the operator simply releases the foot switches to remove the wires and insert more to twist another set.

The PHT comes with everything needed to start twisting wires when it arrives. It comes with:

2ea. 1390-00 Adapter collet assemblies 3/16 id

2ea. 1408-00 Adapter collet assemblies 3/8 id

1ea. 4002-00 Foot switch assembly

1ea. Power cord

1ea. Air coupler Male

1 ea. Operator manual

Requirements

110-120Vac / 5A 110 PSI Max input (Filtered& dry)

Shipping dimensions Box dimensions 18"x18"x28" Standard configuration weight 50LBS

UPS / FedEx typical



Options and accessories

- 7007-00 Spare parts kit
- Extension assemblies for 3/16 id an 3/8 id tubing
- 4600-03 Remote Clamp with two clamps
- 4002-XX, footswitch assemblies for longer wire



For more information and or quote please contact:

The Mello Company Inc. 1819 Firman Dr. Richardson, TX 75081

Ph. (214) 350-7377, Fx. (214) 350-0521, email Sales@TheMelloCompany.com